

Bouly 16

350mA - **required driver see below**

1 x LED array 11W (LED incl.) - 350mA - 1125lm - 2700K - CRI >97


*FALSE ceiling= aperture: Ø67 - depth: min. 100mm (driver in ceiling) / depth: min. 100mm (driver remote)

*CONCRETE ceiling= aperture: Ø67 - depth: min. 150mm (driver remote)

material: transparant glass


* Required free air area, see www.trizo21.com/requiredarea - CEILING - IP50

FALSE ceiling



FALSE ceiling		silver LED HOLDER		BOIN 1600
FALSE ceiling		gold LED HOLDER		BOIN 1608

ACCESSORY FOR CEILING: PLASTER KIT



aperture: Ø122 | PLBO 2000

CONCRETE ceiling



CONCRETE ceiling		silver LED HOLDER		BOIN 1602
CONCRETE ceiling		gold LED HOLDER		BOIN 1680

REQUIRED DRIVER

DEVICE	DIM.	DRIVER	VOLT
1 x	(TRIAC/IGBT)	D 15WT	230V
1 x	(TRIAC/IGBT)	D 18WT	230V
1 x	(PUSH-DIM) + (1-10V)	D 15WP	110V-230V
1 x	(PUSH-DIM) + (DALI)	D 15WDA EU	230V
1 x	(DALI)	D 15WDA EU-US	110V-230V
1-3 x	(PUSH-DIM) + (DALI) + (1-10V)	D 40WDP	110V-230V

driver remote: does not fit through cutout hole of fixture

For warranty use only Trizo21* supplied LED drivers as mentioned. For all specs and techs about drivers, see www.trizo21.com/drivers