


# Wall Down Lite

Cat. No. DL/R Cat. No. DL/GU













# **UK & European Specification**

The Wall Down Lite is suitable for mounting on timber, masonry, stone, etc. non-adjustable for one way wall washing, can be mounted with the lamp directed up or down. Water resistant with a 78mm diameter mounting base, complete with stainless steel screws.

The Retro™ is a 110/240-12 ac mains option suited to an installation where mounting a transformer is a problem, e.g. a brick wall where there is only the cable protruding out of the wall and it is not an option to recess the transformer or when replacing an existing light fitting. The base size increases in size to accommodate the encapsulated IP66 dimmable transformer.

A GU10 version of this luminaire is also available for line voltage lamps. The Wall Down Lite Metal Halide is extremely energy efficient, outputting 2-3 times the light of a halogen lamp, and uses a GX10 20 or 35 watt lamp.

# **Ordering Information**

DL - Wall Down Lite
DL/R - Retro

DL/R - Retro DL/GU - GU10 Material/Finish

BK - Black

BZ - Bronze

GN - Green

STAR - Silver Star

WH - White

WB - Birch

DG - Dark Grey

OG - Olive Green

RG - Beige

COP - Copper SS - 316 Stainless Steel

PR - Primrose

Accessories

CJK - Cable joint Kit
LENSSTEPF - Frosted Lens

GG - Glare Guard

GU - GU10 Option

HCL - Hex Cell Louvre Adaptor

MH - Metal Halide Option /R - Retro Transformer 110 /240-12 Volt

WBAP - Wall Box Adaptor Plate

Example: DL BK

(Accessories ordered separately)

Wall Down Lite

Page 1/3

HUNZA FACTORY

Ph: 64-9-528 9471

130 Felton Mathew Ave Saint Johns Auckland 1072 New Zealand Ph: 64-9-528 9471 Fax: 64-9-528 9361 hunza@hunza.co.nz www.hunza.co.nz

INTERNATIONAL CONTACTS: www.hunza.co.nz/contacts.php

Light Ideas v2 Apr-2016

Specifications may change without notice. Manufactured in New Zealand. © 2014 Hunza Holdings Ltd.



## **Luminaire Construction**

CNC machined from the following metals:

**Body:** High corrosion resistant low copper 63.5mm (2½") x 10mm (25/64") aluminium. End cap - solid aluminium 63.5mm (2½") rod.

# Base & Mounting Plate (Retro™):

Cast from virgin high corrosion resistant CC401 low copper aluminium alloy chromate substrate and high UV resistant polyester powder coat - Black, Bronze, Green, Silver Star, White, Birch, Dar Grey, Olive, Green, Beige, Primrose.

Body: Copper 63.5mm (2½") x 10mm (25/64). End cap - solid copper 63.5mm (2½") rod.

Base: Copper Hand spun 2mm

(5/64")

Mounting Plate: Forged brass (Retro™)

**Body:** 316 Stainless Steel 63.5mm (2½")

x 10mm (25/64) rod. End cap - 316 stainless steel 63.5mm (2½") rod.

**Base:** Investment cast and CNC machined (Retro™).

**Mounting Plate:** Investment cast and CNC machined.

# **Mounting**

12 volt: The luminaire is mounted to the wall using two 316 stainless screws through a shallow base 16mm (5/8") in depth. A Wall Box Adaptor Plate is available as an accessory. Retro™110/240-12 volt: a mounting plate is fixed to the wall using two screws, the luminaire is fitted to the mounting plate.

### **Features**

#### Lens:

10mm (3/8") clear flush fit shatter resistant glass.
Lifetime Warranty.

#### Gaskets:

Silicone, iron impregnated 220°c (428°f)

### Lamp Holder:

GU5.3 & GU10 - 350°c (662°f) ceramic multi contact lamp holder with 250°c (480°f) teflon cables. Metal Halide GX10 - 350°c (662°f) ceramic multi contact lamp holder with 250°c (480°f) teflon cables.

#### Accessories:

Cable Joint Kit (Cat. CJK150)
Frosted Lens (Cat. LENSSTEPF).
Glare Guard (Cat. GG).
Hex Cell Louvre Adaptor (Cat. HCL).
GU10 Option (Cat. GU).
Metal Halide Option (Cat. MH).
Retro™ transformer 110/240-12 volt (Cat. /R).
Wall Box Adaptor Plate (Cat. WBAP).

## **Standards**

IP66 UL1838

# **Luminaire Weight**

12 volt: Alum .460kg (1lb)

Cop 1.200kg (2lb 10oz) SS 1.080kg (2lb 6oz)

Retro: Alum .780kg (1lb 11oz)

Cop 1.680kg (3lb 11oz) SS 1.505kg (3lb 5oz)

# **Power Supply**

HUNZA™ Inground or Wall Mount
Transformer: not included.

Metal Halide - 230-240 volt ac 50Hz
built in ballast

RETRO™

HUNZA™ 110/240-12 volt ac potted electronic transformer built into the Retro™ base. Dimmable with a suitable dimmer.

Approved for internal use.

# **Supplied With**

MR16 GU5.3 20 or 35 watt lamp max. GU10 - GU10 25 or 35 watt lamp max. Metal Halide - GX10 20 or 35 watt lamp





